

Notes

To allow the radio to be powered on while the vehicle is off. **Disclaimer** - Not wiring with an additional switch may cause the vehicle battery to go dead and radio could turn on by itself due to the wireless functionality.

Step-by-step Process

- 1) Disconnect the bullets on the red wire behind the radio.
- 2) Connect a Single Pole Single Throw (SPST) switch in between these bullets (as pictured below).
- 3) Move the red wire of the radio from the accessory post to the battery post on the bus bar.
- 4) Mount the switch somewhere easily accessible. The switch must be turned on any time you want the radio.

